

Wall Mounting Single Input and Single Relay Output Module



The Axis single input and relay output modules are loop powered and designed around a fully digital protocol. Each module allows monitoring of fire alarm and auxiliary devices and provides form C changeover contacts for control of auxiliary devices such as fire shutters.

The input channel is monitored and will detect Normal / Short / Alarm and Open conditions. The output channel is a normally de-energised relay switched on by a command from the control panel.

The unit provides fast alarm and fault signalling, and incorporates a bidirectional short circuit isolator.

Connections are made using plug-in terminal blocks which will accept conductors up to 2.5mm².

The unit is supplied fixed to a plate which is suitable for wall mounting with a choice of standard 25mm or deep 47mm mounting boxes available.

Key Features

- Short circuit isolators in each device to the requirements of EN54-17
- Large capacity, up to 240 devices per loop
- Auto addressing capability (by the control panel) or manually using a hand held programmer
- Digital checking of double address
- Line quality information
- Bicolour (red green) LED driven by the control panel

Specification

Power Supply	15-40 V
Average Current Consumption	I=120 uA
LED Current Consumption	Iled=6mA @24Vdc
Operating Temperature Range	-30°C / +70°C
Humidity (non condensing)	95% RH
Nominal Relay Switching current	I=2A V=30Vdc
End-of-line resistor	(Reol): 27Kohm
Alarm resistor	(Rw): 10Kohm
Dimensions H x W x D mm	85 x 85 x 30
Weight grams	200
IP Rating	21C

Order Codes and Options

20-VMIC120-ADV: Wall Mounting Single Input and Single Relay Output Module