

Description

400-series non-addressable carbon monoxide (CO) gas alarms are suitable for connection to 2-wire and 4-wire non-addressable fire detection control and indicating equipment. 400 detectors can also connect to 2-wire and 4-wire addressable fire detection control and indicating equipment that can accept non-addressable detectors¹.

Advanced electronics in conjunction with a semiconductor gas sensor provide early detection of carbon monoxide gas and high immunity against unwanted alarms.

The 400 CO alarm range provides fire detection and alarm system designers with a Standards-compliant, economical gas detector for life safety and property protection applications.

Features

- Advanced algorithms provide advanced detection discrimination
- Stable gas sensing chamber. No adjustment or replacement required
- High immunity against unwanted alarms
- Surface-mount device (SMD) circuit board design
- 2-wire or 4-wire system operation
- Detector auto-reset once gas levels fall below alarm threshold levels
- Magnet-initiated alarm test function
- DC 12 V or DC 24 V operation
- N/C or N/O alarm relay output
- Loud 85 dB internal sounder
- Audible warning signal of an internal fault
- Easy installation. No programming required
- Connectable to zone monitor for use with addressable control and indicating equipment
- Sleek, low-profile housing design
- Low maintenance



400 non-addressable CO gas alarm

Compliance

400 CO alarms have the following compliance.

	EN 50291 ^{a, c}	UL 2075 ^{b, c}	CE
400-001	✓	✓	✓
400-002	✓	✓	✓
400-003	✓	✓	✓

^a EN 50291 *Electrical apparatus for the detection of carbon monoxide in domestic premises. Test methods and performance requirements*

^b UL 2075 *Gas and Vapor Detectors and Sensors*

^c Third-party conformance assessment has not been undertaken.

Accessories

The following accessories are compatible with 400 CO alarms.

Description	Part number	Datasheet
4-term. 99 mm low profile base ^a	CN1021	31-0036
8-terminal 99 mm low profile base	CN1041	31-0038
Remote indicator ^b	681-001	31-0034
Detector monitor module	620-001	31-0027

^a Suitable for 400-001 only.

^b Requires 8-terminal base.

¹ May be used with the 620-001 detector monitor module.

Specifications

	400-001 400-002	400-003
Operating voltage	DC (10.8 ~ 33) V	DC (10.8 ~ 26.4) V
Start-up current	$\leq 100 \mu\text{A}$	
Start-up time	$\leq 10 \text{ min}$	
Quiescent current	$50 \mu\text{A}$	
Quiescent condition indicator	Flashing red LED every 5 s	
Alarm current (max)	50 mA	
Sampling time	(2 ~ 4) s	
Alarm response threshold	70 $\mu\text{L/L}$ for 60 min ~ 240 min ^a 150 $\mu\text{L/L}$ for 10 min ~ 50 min ^a 400 $\mu\text{L/L}$ for 4 min ~ 15 min ^a 50 $\mu\text{L/L}$ for 60 min ~ 90 min ^b 100 $\mu\text{L/L}$ for 10 min ~ 40 min ^b 300 $\mu\text{L/L}$ for < 3 min ^b	
Alarm condition indicator	Continuous red LED	
Alarm relay	—	SPST. N/O or N/C. 1.0 A @ DC 30 V / 0.5 A @ AC 125 V
Sounder output	$\geq 85 \text{ dB @ } 3 \text{ m}$	
Reset voltage	$\leq 1 \text{ V}$	
Reset time	$\leq 10 \text{ s}$	
Auto reset time	< 30 s	
Internal fault indication	Single short audible signal every 30 s	
Operating temperature	(-10 ~ +40)°C	
Operating humidity	(0 ~ 95)% RH, non-condensing	
Storage temperature	(-25 ~ +70)°C	
Storage humidity	(0 ~ 98)% RH, non-condensing	
Dimensions (excluding contacts)	$\Phi 99 \text{ mm} \times 45 \text{ mm}$	
Ingress protection rating	IP-42	

^a Complies with UL 2075, *Gas and Vapor Detectors and Sensors*.

^b Complies with EN 50291, *Electrical apparatus for the detection of carbon monoxide in domestic premises. Test methods and performance requirements*.

Ordering Information

	2-Wire	4-Wire	Remote Indicator ^a	Relay Output
400-001	✓	—	—	—
400-002	✓	—	✓	—
400-003	—	✓	—	✓

^a Requires 8-terminal base if remote indicator is installed.

View the complete range of products at www.numens.net

