



Addressable Sounder Beacon



Summary

Fully compliant, third party approved sounder beacon. The sounder beacon can be ceiling or wall mounted. It is loop powered and is connected to the loop via just 2 terminals. The sounder beacon can be assigned its own soft address with the use of the handheld programmer (1-324). The sounder beacon can also be set to be a sounder only by use of the same handheld programmer. Provides both visual and audible (up to 86dB) warning by full cause and effect programming on the EA-PXXX range of panels.

Key Points

- Easy installation
- Set as Sounder/Beacon or Sounder only
- Loop powered
- Low consumption
- Fully addressable
- Works with all EA-PXXX panels
- Ceiling or Wall mounted

Technical Specification	
Operating Voltage	Loop 24V (20V ~ 28VDC)
Operating Current - Standby	< 0.2mA
Alarm Current	8mA
Flash Colour	Red
Sound Level	86dB
Programming	Soft addressing (handheld programmer)
Address	Uses 1 Address (range 1 - 324)
Wiring	Loop: two wire
Mounting Hole Distance	45mm ~ 70mm
Material	Flame retardant PC/ABS
Ingress Protection Rating	IP21C
Operating Environment	Temperature range: -10 to 55°C Humidity: 0 to 95% RH, non-condensing
Dimensions	Diameter: 100mm Height: 100.5mm (with base)
Weight	236g(with base)

