



## FireCell Input Output Unit



The FireCell Wireless Input Output unit is quick and easy to install and offers individual addressing at the Fire Control Panel.

Features include; two supervised inputs and two voltage free outputs rated 2A@24V, whilst using only one address on the system.


This device is third party EN certified and compatible with the EMS FireCell system, EMS Fusion Radio Loop Module (RLM) and EMS Wireless Zone Monitor (WZM).


A 230Vac switching Auxiliary Relay Module is also available, for use in conjunction with this device. Refer to doc ref TSD058 for full technical specifications.

### Key Features

- Dual band 868MHz operation
- 2x supervised inputs
- 2x voltage free outputs, rated 2A@24V
- Third party EN certified
- Optional 230Vac switching Auxiliary Relay Module available


### Technical Data


 -10°C to 55°C


 6x AA alkaline batteries

 IP65, indoor use only

 868MHz


 0 - 14 dBm (auto adjusting)


 2x 2A @ 24Vdc rated outputs

 270mm(W) 205mm(H) 75mm(D)

 0.95kg

 **CE 10**  
0359-CPR-0039

 **EN** EN54-18 & EN54-25

 FC-610-001 Dual I/O Unit  
FC-620-001\* Auxiliary Relay Module  
\* for use with FC-610-001