

EST-ISLE

Digital audio RS485 interface

Overview

The EST-ISLE is both a communication module enabling integration with external systems via RS485 protocol, and an audio signal splitter. Address settings – Number of addresses in the range of 0-F (16 addresses).

Local AUDIO IN – 4 input channels on the 8 pin connector. For easier and faster connection of audio sources, Phoenix-type connectors can be used. LOCAL AUDIO IN jack (8 pin connector Phoenix) is bridged with LOCAL AUDIO OUT (RJ-45). Output amplifiers – RJ-45 connector for the 4-channel amplifier.

Local AUDIO OUT – RJ-45 connector for input signals to the system.

PSM – RJ-45 connector for the link with power manager.



EST-ISLE

Digital audio RS485 interface

Technical specifications

Standards & regulation

Standards	EN54-16
-----------	---------

As a company of innovation, UTC Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit UTC Fire & Security online or contact your sales representative.

Last updated on 10 October 2019 - 16:58