

EST-M04

Microphone Station (4 buttons)

Overview

The EST-M04 is a 4 button analog microphone with built in gong, push to talk and bi-color LED indicating the ready-to-speak status.

To operate the device first select the Zones by pressing designated buttons and then press MIC ON button, the status LED will switch from red (not ready for broadcast) to steady green light. In the event of an active built in gong, the status LED will turn green once the gong has ended. When finished transmitting the message release the MIC ON button to deactivate the gooseneck mic.



Details

- Solid construction
- Zone configuration buttons at front panel with LED
- Microphone on/off button with LED
- Flexible microphone neck
- Microphone volume control at rear panel
- Gong feature at rear panel with volume

EST-M04

Microphone Station (4 buttons)

Technical specifications

Electrical

| | |
|-------------------|------------|
| Operating voltage | 20-57 VDC |
| Efficiency | 10 mV / Pa |
| Output level | 775 mV |

Physical

| | |
|---------------------------------|-------------|
| Net weight | 1.2 kg |
| Maximum distance from amplifier | 250 m |
| Recommended cable type | UTP |
| Connector Type | 8P8C (RJ45) |

Standards & regulation

| | |
|-----------|---------|
| Standards | EN54-16 |
|-----------|---------|

As a company of innovation, UTC Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit UTC Fire & Security online or contact your sales representative.